









MX350

6-ZONE MIXER AMPLIFIER, 350W
[100V|8Ω]



-  Speaker Zone Output
-  FM Radio Function
-  USB Player
-  Extended Compatibility
-  Remote Control
-  Microphone Input

The MX350 is a 6-Zone Mixer Amplifier, 350W [100V|8Ω] for your medium to big size installations, You can operate your MX350 @ 4-16Ω or 70V/100V and install it according your needs. With MX350, you can have multiple audio signal solutions USB, Microphone, SD card and radio. This amplifier incorporates a multimedia player that allows you to control and reproduce the USB and SD card.

Product Type

Multi-Zone Mixer Amplifier

Frequency Response (-6dB)

80Hz - 16kHz

Amplifier Technology

AB Class Amplifier

Amplifier Power

350W

Speaker Output

100V | 4Ω - 16Ω

Zones Output

6 Zones

THD+N

<1%

SNR (Signal to Noise Ratio)

Mic: >71dB | Line-in: >85dB

Input Sensitivity

Mic: 3mV (±0.5mV) | Line-in :
300mV(±50mV)

Mixer

7 Channels

Audio Signal Inputs

Microphone | CD Player | USB | SD Card
| FM Radio | BT

Input Connectors

3 x Stereo RCA | 4 x MIC (TS) | USB | SD
Card Slot | FM Antenna (75Ω)

Audio Signal Outputs

Line Audio

Output Connectors

1 x Stereo RCA

Speakers Output Connectors

Low Impedance: Binding Posts | 100V:
Screw Connector

Protections

DC Voltage | Overload | Short-Circuit

Cooling Type

Speed Controlled Fan

Power Input

AC 220V - 240V / 50Hz - 60Hz

Power Consumption

650W (3A)

Special Features

Chime | Ducking | Priority Microphone |
Bass Adjust.: ±10dB (100Hz) | Treble
Adjust.: ±10dB (10kHz)

Fittings

2U 19" Rack

Handles

Two on Front

Construction

Aluminum / Steel

IP Rating

Indoor Use

Dimensions (WxHxD)

483 x 88 x 338mm (19" x 3.5" x 13.3")

Net Weight

16kg (35.3lb)

Shipping Weight

17kg (37.5lb)